



Setting up and Connecting to the Cloud

To get all the features and functionality out of EVO-IP such as iOS/Android mobile app control, remote system monitoring and management, and voice control with Alexa enabled devices, it is important to connect the system to the cloud. There are 2 different ways to create, connect, and use a system based on permissions: one as an INSTALLER which gives full access to the system, and one as an END USER which allows for switching, enabling/disabling of video features.

Setting Up and Connecting as an INSTALLER:

1. Go to: https://www.evo-ip.io/create/installer

← → C △ ● https://www.evo-ip.io/create/installer Cloud CREATE NEW INSTALLER Enter an available email as account example@gmail	
Cloud CREATE NEW INSTALLER Enter an available email as account example@gmail	
CREATE NEW INSTALLER Enter an available email as account example@gmail	
Enter an available email as account example@gmail	
example@gmail	
Please enter your password	
1234ooo	
Please enter your password again	
please enter your password again	
Clear Apply	

2. Enter a valid email address and choose a password.

Cloud	
CREATE NEW INSTALLER	
Enter an available email as acc	
vanco.cloud3@yahoo.com	
Please enter your password	
Please enter your password age	
	Clear Apply
	1
_	
For	chnical Support Call Toll Free: 800-626-6445
	506 Kingsland Dr, Batavia, IL 60510



3. Check your email. Click on the link to verify the email address, and you will be routed back to the evo-ip.io page.

orreply <noreply@evo-ipip.firebaseapp.com> To:</noreply@evo-ipip.firebaseapp.com>	Ē	*
Hello,		
Follow this link to verify your email address.		
https://evo-ipip.firebaseapp.com//auth/action?mode=verifyEmail&oobCode=K_ jPFVx3sTQSoBk4dzgk7ve6SJ/EtKAeVewiki89xiAAAAFmwEorFA&apiKey=AlzaSyDueOfsCj6wLVBLC5j(WA9I2XVIHgYoPa4⟨=en		
If you didn't ask to verify this address, you can ignore this email.		
Thanks,		
Your evo-ip team		
4 , (4 , m) ···		

VOLUTION

4. Once you return to the evo-ip.io page, you will have to add a device (EVOIPCTL1) to your account. You will need 2 numbers to do so: an installer ID number which is found by clicking on your account name on the top right hand side of the window, and the Association number which is found within the Smart Controller GUI.

Installer ID (6 Digits)	
Please enter installelr ID	
Associate Code (6 Digits)	
Please enter associate code	



FVOLUTION

Where to find the Installer ID:

Cloud	III MENU	? No device & vanco.cloud1
R	WELCOME , VANCO.CLOUD1	A Profile
	You Have No Devices Online Yet	Change Password
	To Add Some Device, You Can Follow The Steps Below:	(+ Logout
	1. Click Add Device or Click your name on the right top corner and click 'Add device'	V1.21.75v
	2. Enter installer ID, Associate Code, then click apply	
	3. Enjoy operating your devicet!!	

Where to find the Association Code:



NOTE: This is accessing the Control Box locally, not remotely, and not via the cloud.

GO TO: SMART CONTROLLER (EVO-IP GUI) -> CLOUD (Smart Controller GUI)->STATUS-> GET CODE

NOTE: IF THE ASSOCIATION CODE IS NOT SUBMITTED WITHIN 2 MINUTES, A NEW ASSOCIATION CODE WILL BE NEEDED.

5. Enter these into the appropriate fields, click APPLY and you will be routed to the Cloud and Device(s) homepage. Click on your Profile name to change the name of the EVOIPCTL1 for each job, log into different accounts, change passwords or add other devices/jobs.

For Technical Support Call Toll Free: 800-626-6445 506 Kingsland Dr, Batavia, IL 60510



Evolution

Cloud	a = MENUL		A vanco cloud1
Cloud	MATRIX Presets	SmartControl	Change Name Change Password Add Device
XX Matrix	Display(RX)	Total: 1	✤ Logout D: 514619 √1.21.75v
Video Wal	Preview mode		
	Source(TX)	Total: 2	
Event Access Setup Log	Preview mode 81 TX_024EEB77B9DA &1 82 TX_02E4AF9C565F &0		

6. You can also click on the device name to view, select, and manage other systems connected through the same cloud account and select a favorite to come up when the screen first opens.









Setting Up and Connecting as an END USER:

1. Go to: <u>https://www.evo-ip.io</u>

2. Click on "Create New Account" and then enter the END USER's email and set desired password.

3. Confirm the account by going to the email account used to create the cloud account. Click on the link to verify the email address, and you will be routed back to the evo-ip.io page.

orreply <noreply@evo-ipip.firebaseapp.com> To:</noreply@evo-ipip.firebaseapp.com>	*
Hello,	
Follow this link to verify your email address.	
https://evo-ipip.firehaseapp.com//auth/action?mode=verifyEmail&oobCode=K- jPFVx3sTQSoBk4dZgK7ve6SJIEtKAeVewiiJ69xiAAAAFmwEorFA&apiKey=AlzaSyDueOfsCj6wLVBLC5jIWA9l2XVIHgYoPa4⟨=en	
If you didn't ask to verify this address, you can ignore this email.	
Thanks,	
Your evo-ip team	
(4) (4) (4)	

4. Once you return to the evo-ip.io page, to give the END USER access, click on "Add New Device". Use YOUR Installer ID, and the Association number which is found within the Smart Controller GUI.

Add new device	2
Installer ID (6 Digits)	
Please enter installelr ID	
Associate Code (6 Digits)	
Please enter associate code	
	Close Apply



Evolution

NOTE: YOU NEED TO USE THE INSTALLER ID THAT WAS USED AND PROVIDED WHEN CREATING THE INSTALLER ACCOUNT

Cloud I	E MENU	? No device 🛔 vanco.cloud1
*	WELCOME, VANCO.CLOUD1	Profile
	You Have No Devices Online Yet	Change Password
	To Add Some Device, You Can Follow The Steps Below:	6 Logout
	1. Click Add Device or Click your name on the right top corner and click 'Add device'	V1.21.75v
	2. Enter installer ID, Associate Code, then click apply	

3. Enjoy operating your device!!!

Where to find the Association Code:

	MATR	IX	D 5 mm		
Matrix	Display(RX)		Coud 2	Cloud	
Video Wall		All		Configuration Status	
	Ander 1 hand So de No So			Cloud Status	match pair
Schedule	64 Demo_TV			Association Code	Get Association Code
Event	Source(TX)				
Access	É				
Setup					
	64 Controller	A1 65 Bluray A0			
Smart Controller					

NOTE: This is accessing the Control Box locally, not remotely, and not via the cloud.

GO TO: SMART CONTROLLER (EVO-IP GUI) -> CLOUD (Smart Controller GUI)->STATUS-> GET CODE

NOTE: IF THE ASSOCIATION CODE IS NOT SUBMITTED WITHIN 2 MINUTES, A NEW ASSOCIATION CODE WILL BE NEEDED.

For Technical Support Call Toll Free: 800-626-6445 506 Kingsland Dr, Batavia, IL 60510





5. Click on the USER profile on the upper right hand corner to change the name of the Controller, change Display Name, set favorite device, change password, and add new device.

Cloud	≡ MENU			Franks_Demo	franksvanco
			Presets	SmartControl	Change Name Profile Change Password
	Display(RX)	All	Total:	3 🖬 🖓	Add Device Logout 1.21.78v
Matrix Matrix Video Wall OSD OSD Schedule	Preview mode	Preview mode	Preview mode		
	Source(TX)			Total: 2 🖾	
	Preview mode	Preview mode			

Note that END USER only has access to Matrix, Video Wall, OSD, and Schedule modes only.



