

RAB® Ballast Compatibility List

T8 LED UBent

U6-15-830-DIR
U6-15-835-DIR
U6-15-840-DIR
U6-15-850-DIR

Brand	Part Number	Starting Method	Number of Lamps	Lamp Connection	Nominal Lamp Load		Reduced Lamp Load	
					Input Voltage 120	Input Voltage 277	Input Voltage 120	Input Voltage 277
Philips-Advance	ICN-2P32-N	IS	2	Parallel	✓	✓	✓	✓
	IOP-2P32-N	IS	2	Parallel	✓	✓	✓	✓
	IOP-2P32-LW-N	IS	2	Parallel	✓	✓	✓	✓
	IOPA-4P32-N	IS	4	Parallel	✓	✓	✓	✓
	IOPA-4P32-HL-SC	IS	4	Parallel	✓	✓	✓	✓
	IOP-4P32-N	IS	4	Parallel	✓	✓	✓	✓
	IOP-4P32-LW-N	IS	4	Parallel	✓	✓	✓	✓
	ICN-4P32-N	IS	4	Parallel	✓	✓	✓	✓
	IOPA-2P32-HL-N	IS	2	Parallel	✓	✓	✓	✓
	IOPA-3P32-N	IS	3	Parallel	✓	✓	✓	✓
	IOPA-4P32-SC	IS	4	Parallel	✓	✓	✓	✓
	ICN-132-MC	IS	1	N/A	✓	✓	N/A	N/A
	ICN-2P16-TLED-N	IS	2	Parallel	✓	✓	✓	✓
	ICN-4P16-TLED-N	IS	4	Parallel	✓	✓	✓	✓
	IOP-3PSP32-SC	PS	3	Parallel	✓	✓	✓	✓
	IOP-3PSP32-LW-SC	PS	3	Parallel	✓	✓	✓	✓
	IOP-4PSP32-LW-SC	PS	4	Parallel	✓	✓	✓	✓
OSRAM SYLVANIA	QHE 2X32T8/UNV PSH-HT	PRS	2	Parallel	✓	✓	✓	✓
	QTP 2X32T8/UNV ISN-SC	IS	2	Parallel	✓	✓	✓	✓
	QHE 2X32T8/UNV ISN-SC	IS	2	Parallel	✓	✓	✓	✓
	QHE 2X32T8/UNV ISL-SC	IS	2	Parallel	✓	✓	✓	✓
	QHE 4X32T8/UNV ISN-SC	IS	4	Parallel	✓	✓	✓	✓
	QHE 4X32T8/UNV ISL-SC	IS	4	Parallel	✓	✓	✓	✓
	QTP 3X32T8/UNV ISN-SC	IS	3	Parallel	✓	✓	✓	✓
	QHE 3X32T8/UNV ISN-SC	IS	4	Parallel	✓	✓	✓	✓
	QHE 3X32T8/UNV ISL-SC	IS	3	Parallel	✓	✓	✓	✓
	QHE 1X32T8/UNV ISN-SC	IS	1	N/A	✓	✓	N/A	N/A
	QHE 1X32T8/UNV ISL-SC	IS	1	N/A	✓	✓	N/A	N/A
	QHE 4x32T8/UNV ISH HT-1	IS	4	Parallel	✓	✓	✓	✓
	QTP 2X32T8/UNV ISL-SC	IS	2	Parallel	✓	✓	✓	✓
	QHE 2X32T8/UNV ISH HT-SC	IS	2	Parallel	✓	✓	✓	✓
	QHE 2X32T8/UNV PSN-MC	PRS	2	Parallel	✓	✓	✓	✓
	QHE 3X32T8/UNV PSN-SC	PRS	3	Parallel	✓	✓	✓	✓
	QHE 4X32T8/UNV PSN-SC	PRS	4	Parallel	✓	✓	✓	✓

RAB® Ballast Compatibility List

T8 LED UBent

U6-15-830-DIR
U6-15-835-DIR
U6-15-840-DIR
U6-15-850-DIR

Brand	Part Number	Starting Method	Number of Lamps	Lamp Connection	Nominal Lamp Load		Reduced Lamp Load	
					Input Voltage 120	Input Voltage 277	Input Voltage 120	Input Voltage 277
General Electric	GE-232-MV-N	IS	2	Parallel	✓	✓	✓	✓
	GE232MAX-N/ULTRA	IS	2	Parallel	✓	✓	✓	✓
	GE432MAX-L/ULTRA	IS	4	Parallel	✓	✓	✓	✓
	GE432MAX-G-N	IS	4	Parallel	✓	✓	✓	✓
	GE132MAX-H/ULTRA	IS	1	N/A	✓	✓	N/A	N/A
	GE132MAXP-N/ULTRA	IS	1	N/A	✓	✓	N/A	N/A
	GE232MV-N-DIY	IS	2	Parallel	✓	✓	✓	✓
	GE332MV-N	IS	3	Parallel	✓	✓	✓	✓
	GE332MAX-N/ULTRA	IS	3	Parallel	✓	✓	✓	✓
	GE332MAX-L/ULTRA	IS	3	Parallel	✓	✓	✓	✓
	GE332MAX-G-N	IS	3	Parallel	✓	✓	✓	✓
	GE332MAXP-H/ULTRA	IS	3	Parallel	✓	✓	✓	✓
	GE432MV-N-42T	IS	4	Parallel	✓	✓	✓	✓
	GE432MAX-N/ULTRA	IS	4	Parallel	✓	✓	✓	✓
	GE432MAX90-S60	IS	4	Parallel	✓	✓	✓	✓
	GE232MAX-G-L	IS	2	Parallel	✓	✓	✓	✓
	GE332MAXP-L/ULTRA	IS	3	Parallel	✓	✓	✓	✓
	GE232-MVPS-N	PS	2	Parallel	✓	✓	✓	✓
	GE-332-MVPS-N	PS	3	Parallel	✓	✓	✓	✓
	GE432-MVPS-N	PS	4	Parallel	✓	✓	✓	✓
Universal Lighting Technologies	B232IUNVEL-A	IS	2	Parallel	✓	✓	✓	✓
	B233IUNVHE-A	IS	2	Parallel	✓	✓	✓	✓
	B432IUNVHE L-A	IS	4	Parallel	✓	✓	✓	✓
	B332IUNVHP-A	IS	3	Parallel	✓	✓	✓	✓
	B432IUNVHP-A	IS	4	Parallel	✓	✓	✓	✓
	B132IUNVHP-N	IS	1	N/A	✓	✓	N/A	N/A
	B232IUNVHP-B	IS	2	Parallel	✓	✓	✓	✓
	B232IUNV-C	IS	2	Parallel	✓	✓	✓	✓
	B432IUNVHE-A	IS	4	Parallel	✓	✓	✓	✓
	B432IUNVHEH-E	IS	4	Parallel	✓	✓	✓	✓
HOWARD INDUSTRIES	EP3/32IS/MV/SC/HE	IS	3	Parallel	✓	✓	✓	✓
	EPL4/32IS/MV/MC/HE	IS	4	Parallel	✓	✓	✓	✓
	EPH2/32IS/MV/MC/HE	IS	2	Parallel	✓	✓	✓	✓
	EP4/32IS/MV/MC/HE	IS	4	Parallel	✓	✓	✓	✓
	EPL3/32IS/MV/SC/HE	IS	3	Parallel	✓	✓	✓	✓
	EP3/32IS/MV/MC/HE	IS	3	Parallel	✓	✓	✓	✓
	EP4/32PPRS/MV/SC/HE	PRS	4	Parallel	✓	✓	✓	✓

RAB® Ballast Compatibility List

T8 LED UBent

U6-15-830-DIR
U6-15-835-DIR
U6-15-840-DIR
U6-15-850-DIR

Brand	Part Number	Starting Method	Number of Lamps	Lamp Connection	Nominal Lamp Load		Reduced Lamp Load	
					Input Voltage 120	Input Voltage 277	Input Voltage 120	Input Voltage 277
ESPEN	VE232MVHIPLE	IS	2	Parallel	✓	✓	✓	✓
	VE232MVHIPE	IS	2	Parallel	✓	✓	✓	✓
Halco-ProLume	EP232IS/L/MV/SL	IS	2	Parallel	✓	✓	✓	✓
Halco	EP232IS/MV/HE	IS	2	Parallel	✓	✓	✓	✓
	EP332IS/MV/HE	IS	3	Parallel	✓	✓	✓	✓
	EP432IS/MV/HE	IS	4	Parallel	✓	✓	✓	✓
	EP432IS/L/MV/HE	IS	4	Parallel	✓	✓	✓	✓
	EP232IS/L/MV/HE	IS	2	Parallel	✓	✓	✓	✓
	EP332IS/L/MV/HE	IS	3	Parallel	✓	✓	✓	✓
KEYSTONE	KTEB-232-UV-IS-N-P	IS	2	Parallel	✓	✓	✓	✓
	KTEB-332-UV-IS-N-P	IS	3	Parallel	✓	✓	✓	✓
	KTEB-432-UV-IS-N-P	IS	4	Parallel	✓	✓	✓	✓
	KTEB-232LBF-1-TP-PIC-EV	IS	2	Parallel	✓	N/A	✓	N/A
	KTEB-432RIS-1-TP-SL	IS	4	Parallel	✓	N/A	✓	N/A
	KTEB-332-UV-IS-H-P	IS	3	Parallel	✓	✓	✓	✓
MAXLITE	SKEU324HE/SC	IS	4	Parallel	✓	✓	✓	✓
	SKEU323L/SC	IS	3	Parallel	✓	✓	✓	✓
	MLEU322HEL/SC	IS	2	Parallel	✓	✓	✓	✓
	MLEU323H/SC	IS	3	Parallel	✓	✓	✓	✓
	SKEU322HEL/SC	IS	2	Parallel	✓	✓	✓	✓
	MLEU324HE/SC	IS	4	Parallel	✓	✓	✓	✓
PLUSRITE	BAF232IS/MV	IS	2	Parallel	✓	✓	✓	✓
	BAF332IS/MV	IS	3		✓	✓	✓	✓
	BAF232IS/MV/L	IS	2	Parallel	✓	✓	✓	✓
	BAF332IS/MV/L	IS	3	Parallel	✓	✓	✓	✓
	BAF432IS/MV	IS	4	Parallel	✓	✓	✓	✓
	BAF432IS/MV/L	IS	4	Parallel	✓	✓	✓	✓
EIKO	PM-2X32T8-UNV-IS-L	IS	2	Parallel	✓	✓	✓	✓
	PM-3X32T8-UNV-IS	IS	3	Parallel	✓	✓	✓	✓
	PM-3X32T8-UNV-IS-L	IS	3	Parallel	✓	✓	✓	✓
	PM-4X32T8-UNV-IS	IS	4	Parallel	✓	✓	✓	✓

RAB® Ballast Compatibility List

T8 LED UBent

U6-15-830-DIR
U6-15-835-DIR
U6-15-840-DIR
U6-15-850-DIR

Brand	Part Number	Starting Method	Number of Lamps	Lamp Connection	Nominal Lamp Load		Reduced Lamp Load	
					Input Voltage 120	Input Voltage 277	Input Voltage 120	Input Voltage 277
EIKO	PM-4X32T8-UNV-IS-L	IS	4	Parallel	✓	✓	✓	✓
	PM-2X32T8-UNV-IS	IS	2	Parallel	✓	✓	✓	✓
	PM-2x32T8-UNV-IS-H	IS	2	Parallel	✓	✓	✓	✓
TCP	E3P32ISUNVE	IS	3	Parallel	✓	✓	✓	✓
	E3P32ISUNVLE	IS	3	Parallel	✓	✓	✓	✓
	E4P32ISUNVE	IS	4	Parallel	✓	✓	✓	✓
	TCP3P32ISUNVH	IS	3	Parallel	✓	✓	✓	✓
SOLA	E-758-U-232-MC	IS	2	Parallel	✓	✓	✓	✓
Fulham-WORK HORSE	WHSG3-UNV-T8-IS	IS	3	Parallel	✓	✓	✓	✓
	WHSG4-UNV-T8-IS	IS	4	Parallel	✓	✓	✓	✓
SUNPARK	120-1/32IS HPF	IS	1	N/A	✓	N/A	N/A	N/A
	U-2/32IS HBF	IS	2	Parallel	✓	✓	✓	✓
	U-2/32ISE-LBF	IS	2	Parallel	✓	✓	✓	✓
	U-3/32ISE	IS	3	Parallel	✓	✓	✓	✓
	U-3/32ISE-HBF	IS	3	Parallel	✓	✓	✓	✓
	U-4/32IS HP,F	IS	4	Parallel	✓	✓	✓	✓
	U-4/32IS HBF	IS	4	Parallel	✓	✓	✓	✓
	U-4/32ISE-LBF	IS	4	Parallel	✓	✓	✓	✓
	LC 12011T	RS	1	N/A	✓	N/A	N/A	N/A
	U-1/32PSE	PS	1	N/A	✓	✓	N/A	N/A
HATCH	HL232BIS/UV/HE/W	IS	2	Parallel	✓	✓	✓	✓
	HL432BIS/UV/HE/W	IS	4	Parallel	✓	✓	✓	✓
ARCATA	ACT 3P32ISUNVLE	IS	3	Parallel	✓	✓	✓	✓
LIGHTING PRODUCTS LIMITED	EB-332EBF-UV-TP-HE	IS	3	Parallel	✓	✓	✓	✓
TOPAZ	B432IUNVHEH/A-TPZ	IS	4	Parallel	✓	✓	✓	✓
DAMAR	EL232HL-120/277HF(1688D)	IS	2	Parallel	✓	✓	✓	✓
	EL332-120/277HF(3654C)	IS	3	Parallel	✓	✓	✓	✓
	EL332HL-120/277HF(3654H)	IS	3	Parallel	✓	✓	✓	✓
	EL432-120/277HF(3093B)	IS	4	Parallel	✓	✓	✓	✓

T8 LED UBent

U6-15-830-DIR
U6-15-835-DIR
U6-15-840-DIR
U6-15-850-DIR

					Nominal Lamp Load		Reduced Lamp Load	
Brand	Part Number	Starting Method	Number of Lamps	Lamp Connection	Input Voltage 120	Input Voltage 277	Input Voltage 120	Input Voltage 277
Waltran	DB-232N-MV-TP-HE	IS	2	Parallel	✓	✓	✓	✓
	DB-332N-MV-TP-HE	IS	3	Parallel	✓	✓	✓	✓
	DB-432N-MV-TP-HE	IS	4	Parallel	✓	✓	✓	✓
	DB-432L-MV-TP-HE	IS	4	Parallel	✓	✓	✓	✓
ACT	ACT 2P32ISUNVE	IS	2	Parallel	✓	✓	✓	✓
ANTRON ELECTRONICS	A32T8MICLO	IS	2	Parallel	✓	✓	✓	✓
Superior Life	70210	PS	2	Parallel	✓	✓	✓	✓
	70211	PS	4	Parallel	✓	✓	✓	✓